

Intel® Cluster Studio 2013 Service Pack 1 (SP1) Update 1 Release Notes

Document number: 327993-003US
20 January 2014

Contents

[Introduction](#)
[Product Contents](#)
[What's New](#)
[System Requirements](#)
[Installation Notes](#)
[Documentation](#)
[Issues and Limitations](#)
[Technical Support](#)
[Legal Information](#)

Introduction

Intel® Cluster Studio for Linux* OS and Windows* OS accelerates parallel software development on cluster systems based on IA-32 and Intel® 64 architectures, as well as Intel® Many Integrated Core Architecture (Intel® MIC Architecture) on Linux* OS. For Intel® MIC Architecture, only Intel® Xeon Phi™ coprocessor (codename: Knights Corner) is supported.

Intel® Cluster Studio supports application development using Intel® MPI Library with optimized parallel libraries, performance analysis, and benchmarks. Intel® Cluster Studio saves software developers time and improves performance on distributed computing systems.

Intel® Cluster Studio for Linux* OS and Windows* OS supports critical parts of the message-passing interface (MPI) application development process including:

- Compiler support through Intel® C++ Compiler XE and Intel® Fortran Compiler XE. Intel® C++ Compiler XE and Intel® Fortran Compiler XE for Linux* OS provide support for Intel® Many Integrated Core Architecture (Intel® MIC Architecture).
- Intel® MPI Library 4.1 Update 3, which implements the Message Passing Interface 2.2 Standard (MPI-2.2). Intel MPI library enables multiple interconnect solutions with a single implementation. Intel® MPI Library for Linux* OS supports Intel® Many Integrated Core Architecture (Intel® MIC Architecture).
- Intel® Trace Analyzer and Collector 8.1 Update 4

- o Intel® Trace Collector provides event-based tracing in cluster applications through an instrumentation library that ensures low overhead in execution. The trace information provides performance data, statistics, multi-threaded events, and automatic instrumentation of user binaries on Intel® 64, IA-32 and Intel® Many Integrated Core Architecture (Intel® MIC Architecture).
 - o Intel® Trace Analyzer provides visual analysis of application activities gathered by the Intel Trace Collector.
 - o A message checking component of the Intel Trace Collector provides a novel MPI correctness technology that detects errors with data types, buffers, communicators, point-to-point messages and collective operations, deadlocks, and data corruption.
- Application tuning with optimized mathematical library functions from Intel® Math Kernel Library (Intel® MKL) that includes ScaLAPACK* solvers and Cluster DFTs (Discrete Fourier Transforms). Intel® MKL for Linux* OS supports Intel® Many Integrated Core Architecture (Intel® MIC Architecture).
 - Intel® MPI Benchmarks that makes it easy to gather performance information about a cluster system.

On completing the Intel® Cluster Studio installation process, locate the `Doc_Index.htm` file in the `doc` folder on the master node of the cluster. This file is a documentation map to navigate to various information resources of the Intel® Cluster Studio.

[Back to Top](#)

Product Contents

The table below lists the product components and related documentation.

Component	Version	Documentation
Intel® C++ Compiler XE	14.0 Update 2	get_started_wc.htm for Windows* OS get_started_lc.htm for Linux* OS
Intel® Debugger (Linux* OS only)	13.0 Update 1	debugger_documentation.htm
Intel® Fortran Compiler XE	14.0 Update 2	get_started_wc.htm for Windows* OS get_started_lc.htm for Linux* OS
Intel® Integrated Performance Primitives (Intel® IPP)	8.1	ipp_documentation.htm
Intel® Math Kernel Library (Intel® MKL)	11.1 Update 2	mkl_documentation.htm

Intel® MPI Benchmarks	3.2 Update 4	IMB_Users_Guide.htm Readme_Addendum_for_MIC_Architecture.txt (Linux* OS only)
Intel® MPI Library	4.1 Update 3	Doc_Index.html for Linux* OS and Doc_Index.htm for Windows* OS
Intel® Threading Building Blocks (Intel® TBB)	4.2 Update 3	tbb_documentation.htm
Intel® Trace Analyzer and Collector	8.1 Update 4	ITA_Reference_Guide.htm ITC_Reference_Guide.htm
GNU* Project Debugger (GDB*) (GPL licensed)	7.5	
Microsoft* Visual Studio* Shell for Intel® Visual Fortran (For Windows* OS; installs only on the master node)		NOTE: Intel® Cluster Studio for Windows* OS provides Microsoft* Visual Studio* 2010 Shell. As a prerequisite, if you install the included Microsoft Visual Studio 2010 Shell, additional Microsoft software may be required to be installed prior to beginning the installation of Intel® Cluster Studio. Microsoft .NET* 4.0 Framework is required for Microsoft Visual Studio 2010 Shell. If you do not have this framework installed already, you can download the installer from: http://www.microsoft.com/en-us/download/details.aspx?id=17851

[Back to Top](#)

What's New

This section highlights important changes from the previous product version. For information on what is new in each component, please read the individual component release notes.

Changes since Intel® Cluster Studio 2013 SP1:

- All components updated to current versions
- 32 Bit Support of Intel® MPI Library & Intel® Trace Analyzer and Collector is deprecated. For details, see <http://software.intel.com/en-us/articles/intel-cluster-tools-deprecation-information>.

[Back to Top](#)

System Requirements

Processor Requirements

Systems based on IA-32 architecture:

A system based on the Intel® Pentium® 4 processor or higher

Intel® Core® i7 processor recommended

Systems based on Intel® 64 architecture:

Intel® Core™ processor family or higher

Intel® Xeon® 5500 processor series recommended

Note: It is assumed that the processors listed above are configured into homogeneous clusters. For Windows* OS, only processors based on the Intel® 64 architecture are supported.

[Back to Top](#)

Disk Space Requirements

100 GB of disk space (minimum)

Note: During the installation process, the installer may need up to 12 GB of temporary disk storage to manage the intermediate installation files.

[Back to Top](#)

Operating System Requirements

OS Distributions	IA-32 Architecture	Intel® 64 Architecture	
		32-Bit Applications	64-Bit Applications
Intel® Cluster Ready ¹	N/A	N/A	S
Red Hat Enterprise Linux* 5.0	S	S	S
Red Hat Enterprise Linux* 6.0	S	S	S
SUSE Linux Enterprise Server* 11	S	S	S
Microsoft* Windows* HPC Server 2008	N/A	S	S
Microsoft* Windows* HPC Server 2008 R2	N/A	S	S

S = Supported

Microsoft Windows HPC Server 2008 and Microsoft Windows HPC Server 2008 R2 operating systems support only Intel® 64 architecture.

¹ Intel® Cluster Ready is an applications platform architecture standard for Linux* OS clusters. Please convey to your users the Linux* platform needed for your MPI application with:

This application has been verified to run correctly on Linux* OS clusters that conform to the Intel® Cluster Ready platform architecture. Each Intel® Cluster Ready system is shipped and tested with a diagnostic tool: Intel® Cluster Checker. Intel® Cluster Checker is used to validate operability and compliance, as well as overall system health. On an Intel® Cluster Ready system, start with these commands to easily view diagnostic logs:

```
$ . /opt/intel/clck/<version>/clckvars.sh  
$ cluster-check --report
```

For more information on Intel® Cluster Ready and on the alliance of partner vendors, please visit <http://www.intel.com/go/cluster>.

[Back to Top](#)

Memory Requirements

2 GB RAM (minimum)

[Back to Top](#)

Intel® Professional Edition C++ Compiler and Intel® Fortran Compilers

For all of the Intel® architectures, the version number on the Intel compilers should be 11.1 or higher.

[Back to Top](#)

Adobe* Reader*

There are certain documents within the Intel® Cluster Studio that require Adobe* Reader* for viewing. You can download Adobe Reader onto your system from <http://get.adobe.com/reader/>

[Back to Top](#)

Installation Notes

For instructions on installing and uninstalling the Intel® Cluster Studio 2013 on Linux* OS and Windows* OS, see the Installation Guide.

[Back to Top](#)

Documentation

The documentation index file Doc_Index.htm provides hyperlinks to the Intel® Cluster Studio

documentation.

[Back to Top](#)

Issues and Limitations

1. When trying to install the Intel® Cluster Studio via the "*activate by using a license manager*" option, you may experience delays of up to 10 minutes. Do not immediately shut down the install in such cases but wait for the installer to complete. If you experience delays exponentially longer than this, contact Intel® Premier Support at <http://premier.intel.com>
2. There have been situations where during the installation process, /tmp has been filled up. We recommend that you have **at least 12 GB of free space** in /tmp when installing the Intel® Cluster Studio. Also, the installer script `install.sh` has the command-line options:

```
-t [FOLDER]
```

or

```
--tmp-dir [FOLDER]
```

where `[FOLDER]` is a directory path, which can direct the use of intermediate storage to another disk partition referenced by `[FOLDER]`. `[FOLDER]` should be a non-shared storage location on each node of the cluster. Note that `[FOLDER]` should also contain **at least 12 GB of free space**.

3. On Linux* OS, if any software component of the Intel® Cluster Studio is detected as pre-installed on the head node, that software component will not be processed by the Intel Cluster Studio installer. There is a similar problem on Windows* OS in the 'Modify' mode. For Windows* OS, if some software component of the Intel® Cluster Studio is pre-installed on the head node using the Intel Cluster Studio installer, that software component will not be installed on the compute nodes of the cluster. For either Linux* OS or Windows* OS, if you already installed some of the software components only on the head node, and you want to install them on the other nodes using the Intel Cluster Studio installer, you need to uninstall such components from the head node manually before starting the installer.
4. For Linux* OS versions of the Intel® Cluster Studio, the Java* Runtime Environment is used by the Intel® Debugger graphical environment, which is a Java* application. On Linux* OS, the installer may display the following message with respect to the Java* Runtime Environment (JRE) during installation:

```
Step no: 4 of 6 | Installation configuration > Missing Optional Prerequisite
```

```
-----  
There is one or more optional unresolved issues. It is highly recommended to fix  
them all before you continue the installation. You can fix it without exiting  
the installation and re-check. Or you can quit the installation, fix the  
issues, and  
run the installation again.  
-----
```

```
Missing optional prerequisite
```

-- No compatible Java* Runtime Environment (JRE) found

-
1. Skip missing optional prerequisites [default]
 2. Show the detailed info about issue(s)
 3. Re-check the prerequisites

- h. Help
- b. Back to the previous menu
- q. Quit

Please type a selection or press "Enter" to accept default choice [1]:

You can resolve this issue by entering value 2 after the prompt message for the installation state shown above. This will generate the following diagnostic information:

Step no: 4 of 6 | Installation configuration > Missing Optional Prerequisite

This system does not appear to have a Java* JRE version 5.0 (also referred to as 1.5.0) installed. This may prevent operation of the Intel(R) Debugger GUI. For further details, please refer to the System Requirement section of the product Release Notes.

-
1. Finish with prerequisites and continue installation [default]
 2. Back to Prerequisite summary dialog

- h. Help
- b. Back to the previous menu
- q. Quit

Please type a selection or press "Enter" to accept default choice [1]:

The generated instructions indicate that the Java* Runtime Environment is missing from your system. For the prompt message above, enter the character "q" to quit the installation process. Make sure that the Java* Runtime Environment package is installed on your system. The directory path for the Java* Runtime Environment might be:

/usr/java

If you cannot find the Java* Runtime Environment library on your system, you can download the appropriate version of the Java* Runtime Environment from: <http://www.java.com/en/download/>

After the download completes, install the Java* Runtime Environment on your system. You may need a system administrator to help you with the installation. The Java* Runtime Environment is used by the Intel® Debugger graphical environment which is a Java* application.

Once you have a compatible Java* Runtime Environment library on your system, set your

PATH environment variable to include the directory path to the Java* Runtime Environment library. The Bourne* and Korn* Shell syntax for setting the PATH environment variable might be as follows:

```
export PATH=/usr/java/jre1.5.0_22/bin:$PATH
```

For C Shell, the syntax for setting the PATH environment variable might be as follows:

```
setenv PATH /usr/java/jre1.5.0_22/bin:$PATH
```

After setting the PATH environment variable, repeat the installation process. The message regarding the missing Java* Runtime Environment library will disappear.

5. Intel® Cluster Studio for Windows* OS requires **the creation and use of symbolic links for installation of the Intel software product components**. If you have a File Allocation Table (FAT32) file system deployed on your Windows* OS platform, these symbolic links cannot be created and the integrity of the Intel® Cluster Studio installation is compromised.

6. Intel® Trace Analyzer and Collector - itcpin is not supported for Linux* OS kernels version 3.x.

7. For Intel® MIC Architecture, Intel® MPI Library for Linux* OS supports only Intel® Xeon Phi™ coprocessor (codename: Knights Corner).

This release of the Intel® MPI Library for Linux* OS does not support certain features for Intel® Xeon Phi™ coprocessor:

- o MPD process manager

Intel® MPI Library for Linux* OS supports multiple DAPL* providers for communication between the host and the Intel® Xeon Phi™ coprocessor and between several Intel® Xeon Phi™ coprocessors inside one node.

Currently supported providers are DAPL over InfiniBand* Architecture and DAPL over Intel® Symmetric Communication Interface (Intel® SCI). This feature requires using symbolic names in the host file.

[Back to Top](#)

Technical Support

Your feedback is very important to us. To receive technical support for the tools provided in this product and technical information including FAQ's and product updates, you need to register for an Intel® Premier Support account at the [Intel® Registration Center](#).

Note: Registering for support varies for release product or pre-release products (alpha, beta, etc) - only released software products have support web pages at <http://software.intel.com/sites/support/>.

To register for an account, please visit the Intel® Registration Center website at <http://www.intel.com/software/products/registrationcenter/index.htm>. If you have forgotten your password, please email a request to: quadsupport@mailbox.intel.com. Please do not email your technical issue to this email address.

The product support web site, located under the SUPPORT tab of the <http://www.intel.com/go/clustertools> product page, provides top technical issues, FAQs & Known Issues, [Documentation](#) and Training, and product errata. For more information, and to connect with the Intel HPC community, visit the Intel® Cluster Studio XE forums: <http://software.intel.com/en-us/forums/intel-clusters-and-hpc-technology>.

Submitting Issues

To submit an issue via the Intel Premier Support website, please perform the following steps:

1. Ensure that Java* and JavaScript* are enabled in your browser.
2. Go to <https://premier.intel.com/>.
3. Type in your Login and Password. Both are case-sensitive.
4. Accept the "Confidentiality Statement" if prompted. You will only have to do this the first time you log in.
5. Click the "Submit Issue" button in the upper right corner.
6. Search for a product (e.g. "Cluster Studio") and select from the dynamic drop-down list. Hit Next.
7. Complete the fields and enter a description of your issue. You may attach a log file or a reproducer at this time. Hit Next.
8. Review the text you have entered and hit Submit.

Follow these guidelines when forming your problem report or product suggestion:

1. Describe your difficulty or suggestion. For problem reports, please be as specific as possible (for example, including compiler and link command line options), so that we may reproduce the problem. Please include a small test case if possible.
2. Describe your system configuration information. Be sure to include specific information that may be applicable to your setup: operating system, name and version number of the installed applications, and anything else that may be relevant to helping us address your concern.

[Back to Top](#)

Legal Information

INFORMATION IN THIS DOCUMENT IS PROVIDED IN CONNECTION WITH INTEL PRODUCTS. NO LICENSE, EXPRESS OR IMPLIED, BY ESTOPPEL OR OTHERWISE, TO ANY INTELLECTUAL PROPERTY RIGHTS IS GRANTED BY THIS DOCUMENT. EXCEPT AS PROVIDED IN INTEL'S TERMS AND CONDITIONS OF SALE FOR SUCH PRODUCTS, INTEL ASSUMES NO LIABILITY WHATSOEVER AND INTEL DISCLAIMS ANY EXPRESS OR IMPLIED WARRANTY, RELATING TO SALE AND/OR USE OF INTEL PRODUCTS INCLUDING LIABILITY OR WARRANTIES RELATING TO FITNESS FOR A PARTICULAR PURPOSE, MERCHANTABILITY, OR INFRINGEMENT OF ANY PATENT, COPYRIGHT OR OTHER INTELLECTUAL PROPERTY RIGHT.

A "Mission Critical Application" is any application in which failure of the Intel Product could result, directly or indirectly, in personal injury or death. SHOULD YOU PURCHASE OR USE INTEL'S

PRODUCTS FOR ANY SUCH MISSION CRITICAL APPLICATION, YOU SHALL INDEMNIFY AND HOLD INTEL AND ITS SUBSIDIARIES, SUBCONTRACTORS AND AFFILIATES, AND THE DIRECTORS, OFFICERS, AND EMPLOYEES OF EACH, HARMLESS AGAINST ALL CLAIMS COSTS, DAMAGES, AND EXPENSES AND REASONABLE ATTORNEYS' FEES ARISING OUT OF, DIRECTLY OR INDIRECTLY, ANY CLAIM OF PRODUCT LIABILITY, PERSONAL INJURY, OR DEATH ARISING IN ANY WAY OUT OF SUCH MISSION CRITICAL APPLICATION, WHETHER OR NOT INTEL OR ITS SUBCONTRACTOR WAS NEGLIGENT IN THE DESIGN, MANUFACTURE, OR WARNING OF THE INTEL PRODUCT OR ANY OF ITS PARTS.

Intel may make changes to specifications and product descriptions at any time, without notice. Designers must not rely on the absence or characteristics of any features or instructions marked "reserved" or "undefined". Intel reserves these for future definition and shall have no responsibility whatsoever for conflicts or incompatibilities arising from future changes to them. The information here is subject to change without notice. Do not finalize a design with this information.

The products described in this document may contain design defects or errors known as errata which may cause the product to deviate from published specifications. Current characterized errata are available on request.

Contact your local Intel sales office or your distributor to obtain the latest specifications and before placing your product order.

Copies of documents which have an order number and are referenced in this document, or other Intel literature, may be obtained by calling 1-800-548-4725, or go to: <http://www.intel.com/design/literature.htm>

MPEG-1, MPEG-2, MPEG-4, H.261, H.263, H.264, MP3, DV, VC-1, MJPEG, AC3, AAC, G.711, G.722, G.722.1, G.722.2, AMRWB, Extended AMRWB (AMRWB+), G.167, G.168, G.169, G.723.1, G.726, G.728, G.729, G.729.1, GSM AMR, GSM FR are international standards promoted by ISO, IEC, ITU, ETSI, 3GPP and other organizations. Implementations of these standards, or the standard enabled platforms may require licenses from various entities, including Intel Corporation.

BlueMoon, BunnyPeople, Celeron, Celeron Inside, Centrino, Centrino Inside, Cilk, Core Inside, E-GOLD, Flexpipe, i960, Intel, the Intel logo, Intel AppUp, Intel Atom, Intel Atom Inside, Intel CoFluent, Intel Core, Intel Inside, Intel Insider, the Intel Inside logo, Intel NetBurst, Intel NetMerge, Intel NetStructure, Intel SingleDriver, Intel SpeedStep, Intel Sponsors of Tomorrow., the Intel Sponsors of Tomorrow. logo, Intel StrataFlash, Intel vPro, Intel Xeon Phi, Intel XScale, InTru, the InTru logo, the InTru Inside logo, InTru soundmark, Itanium, Itanium Inside, MCS, MMX, Pentium, Pentium Inside, Puma, skool, the skool logo, SMARTi, Sound Mark, Stay With It, The Creators Project, The Journey Inside, Thunderbolt, Ultrabook, vPro Inside, VTune, Xeon, Xeon Inside, X-GOLD, XMM, X-PMU and XPOSYS are trademarks of Intel Corporation in the U.S. and/or other countries.

* Other names and brands may be claimed as the property of others.

Microsoft, Windows, and the Windows logo are trademarks, or registered trademarks of Microsoft Corporation in the United States and/or other countries.

Java is a registered trademark of Oracle and/or its affiliates.

Copyright © 2010-2014, Intel Corporation. All rights reserved.

Optimization Notice

Intel's compilers may or may not optimize to the same degree for non-Intel microprocessors for optimizations that are not unique to Intel microprocessors. These optimizations include SSE2, SSE3, and SSSE3 instruction sets and other optimizations. Intel does not guarantee the availability, functionality, or effectiveness of any optimization on microprocessors not manufactured by Intel. Microprocessor-dependent optimizations in this product are intended for use with Intel microprocessors. Certain optimizations not specific to Intel microarchitecture are reserved for Intel microprocessors. Please refer to the applicable product User and Reference Guides for more information regarding the specific instruction sets covered by this notice.

Notice revision #20110804

[Back to Top](#)
